

-EXPERIENCE electronics- power transformer data sheet NTR-P\3 A

Power transformer for circlotron stereo amplifiers with power rating up to 2 x 50 W. Recommended tube types EL 34, 6L6 GC, KT 88, 6550 A and similar ones.

| | | |
|----------------|---|----------------|
| Power handling | 210 VA | pinning |
| Primary | 115 V 115 V | (1-2) (3-4) |
| Secondary 1 | 6.3 V/3.7 A | (6-7) |
| Secondary 2 | 6.3 V/3.7 A | (8-9) |
| Secondary 3 | 50 V/0.02 A | (11-12) |
| Secondary 4 | 50 V/0.02 A | (13-14) |
| Secondary 5 | 50 V/0.02 A | (15-16) |
| Secondary 6 | 50 V/0.02 A | (17-18) |
| Secondary 7 | 310 V/0.13 A | (20-21) |
| Secondary 8 | 310 V/0.13 A | (23-24) |
| Secondary 9 | 310 V/0.13 A | (26-27) |
| Secondary 10 | 310 V/0.13 A | (29-30) |
| Core type | MD 102 A | |
| Dimensions | length 120 mm width 102 mm height 71 mm | |
| Mounting | bolts M 5 | |
| Weight | ca. 3.5 kg | |
| Connectors | solder lugs | |

